

# CEA Standard

## Wireless Power Glossary of Terms

CEA-2042.1-A

June 2012



**CEA**<sup>®</sup>  
Consumer Electronics Association

[www.CE.org](http://www.CE.org)

## NOTICE

Consumer Electronics Association (CEA<sup>®</sup>) Standards, Bulletins and other technical publications are designed to serve the public interest through eliminating misunderstandings between manufacturers and purchasers, facilitating interchangeability and improvement of products, and assisting the purchaser in selecting and obtaining with minimum delay the proper product for his particular need. Existence of such Standards, Bulletins and other technical publications shall not in any respect preclude any member or nonmember of CEA from manufacturing or selling products not conforming to such Standards, Bulletins or other technical publications, nor shall the existence of such Standards, Bulletins and other technical publications preclude their voluntary use by those other than CEA members, whether the standard is to be used either domestically or internationally.

Standards, Bulletins and other technical publications are adopted by CEA in accordance with the American National Standards Institute (ANSI) patent policy. By such action, CEA does not assume any liability to any patent owner, nor does it assume any obligation whatever to parties adopting the Standard, Bulletin or other technical publication.

This document does not purport to address all safety problems associated with its use or all applicable regulatory requirements. It is the responsibility of the user of this document to establish appropriate safety and health practices and to determine the applicability of regulatory limitations before its use.

This document is copyrighted by the Consumer Electronics Association (CEA<sup>®</sup>) and may not be reproduced, in whole or part, without written permission. Federal copyright law prohibits unauthorized reproduction of this document by any means. Organizations may obtain permission to reproduce a limited number of copies by entering into a license agreement. Requests to reproduce text, data, charts, figures or other material should be made to CEA.

(Formulated under the cognizance of the CEA **R6.3 Wireless Power Subcommittee.**)

Published by  
©CONSUMER ELECTRONICS ASSOCIATION 2012  
Technology & Standards Department  
[www.CE.org](http://www.CE.org)

All rights reserved

## **FOREWORD**

This document was developed by the Consumer Electronics Association (CEA) R6.3, Wireless Power Subcommittee.

This page is intentionally blank.

## CONTENTS

<b>1 Scope.....</b>	<b>1</b>
<b>2 Terms &amp; Definitions .....</b>	<b>1</b>

This page is intentionally blank.

## Wireless Power Glossary of Terms

### 1 Scope

This document specifies terms and definitions for wireless power.

### 2 Terms & Definitions

<b>Term</b>	<b>Definition</b>
<b>Alignment Aid</b>	A method of positioning a receiver relative to a transmitter that provides the user with feedback to properly align the active area of the receiver to the active area of the transmitter.
<b>Authentication</b>	The process of validating that a proper receiver has been placed within proximity before power is transmitted. Without a proper validation, power should not be transmitted.
<b>Battery Management System (BMS)</b>	A system of circuits (may be integrated with a battery into a "battery pack") to monitor key operational parameters of a battery during charging and discharging, e.g. voltages, currents, internal temperature of the battery, ambient temperature. The monitoring circuits may provide inputs to protection devices which would generate alarms or disconnect the battery from the load or charger should any of the parameters become out of limits.
<b>Charging Region</b>	The area from where power is made available to receivers. (e.g., a charging pad is one example of a charging region)
<b>Communication Protocol</b>	A formal description of digital message formats and the rules a receiver and a transmitter follow for exchanging those messages for wireless power transfer. This may include signaling, compliance verification and error detection/correction capabilities and may also be implemented in hardware, software or both.
<b>Conductive Wireless Power Systems</b>	These systems allow wire-free power delivery. A wireless power system that provides a conductive surface to which receivers are connected through direct electrical contacts.
<b>Coupling Coefficient (k)</b>	$K = M / \text{SQRT}(L1 \times L2)$ <ul style="list-style-type: none"> <li>• Where M is the Mutual Inductance, and</li> <li>• L1 and L2 are the inductance of first and second coil, respectively</li> </ul>
<b>Device Detection</b>	The process by which a transmitter identifies that a receiver is within proximity of the transmitter.
<b>Electromagnetic</b>	The properties of interdependent, time-varying electric and magnetic fields.
<b>Electromagnetic Induction (aka Magnetic Induction)</b>	The production of a current within, and transfer of, voltage across a conductor moving through a magnetic field or, alternatively, a magnetic field moving through a conductor without wires or metal contacts.